

General information

Standard thermal overload relays

Standard – Thermal, Type TA, Class 10 & Electronic, Type E, Class 10, 20 & 30



A9



A50

For contactor	Setting range A	Suffix code for all other starters	Catalog number
A/AE9 – A/AE40 BC9 – BC30	0.1 – 0.16	A	TA25DU0.16
	0.16 – 0.25	B	TA25DU0.25
	0.25 – 0.4	C	TA25DU0.4
	0.4 – 0.63	D	TA25DU0.63
	0.63 – 1.0	E	TA25DU1.0
	1.0 – 1.4	F	TA25DU1.4
	1.3 – 1.8	G	TA25DU1.8
	1.7 – 2.4	H	TA25DU2.4
	2.2 – 3.1	J	TA25DU3.1
	2.8 – 4.0	K	TA25DU4.0
	3.5 – 5.0	L	TA25DU5.0
	4.5 – 6.5	M	TA25DU6.5
	6.0 – 8.5	N	TA25DU8.5
	7.5 – 11	P	TA25DU11
10 – 14	Q	TA25DU14	
13 – 19	R	TA25DU19	
18 – 25	S	TA25DU25	
24 – 32	T	TA25DU32	
A/AE30 – A/AE40	18 – 25	A	TA42DU25
	22 – 32	B	TA42DU32
	29 – 42	C	TA42DU42
A/AE/AF50 – A/AE/AF75	18 – 25	A	TA75DU25
	22 – 32	B	TA75DU32
	29 – 42	C	TA75DU42
	36 – 52	D	TA75DU52
	45 – 63	E	TA75DU63
	60 – 80	F	TA75DU80
A/AE/AF95 – A/AE/AF110	29 – 42	C	TA80DU42
	36 – 52	D	TA80DU52
	45 – 63	E	TA80DU63
	60 – 80	F	TA80DU80
	65 – 90	A	TA110DU90
	80 – 110	B	TA110DU110
A/AF145 – A/AF185	65 – 90	A	TA200DU90
	80 – 110	B	TA200DU110
	100 – 135	C	TA200DU135
	110 – 150	D	TA200DU150
	130 – 175	E	TA200DU175
	150 – 200	F	TA200DU200
A/AF210 – A/AF300	130 – 185	A	TA450DU185 ①
	165 – 235	B	TA450DU235
	220 – 310	C	TA450DU310
A/AF400 – A/AF460	170 – 500	E5	E500DU500 ②
A/AF580 – A/AF750	270 – 800	E8	E800DU800 ②

① TA450 overloads require mounting kits for installation.

② Not suitable for single-phase motors or direct current (DC) motors.